

## ALR720 - 7" Tablet Specification



Model		
7"	ALR720	
PCBA	G78AF	
Hardware		
CPU	1.5GHz Dual Core CPU	
GPS (optional)	ublox max 7	
3G module / GPRS module (optional)	Telit UL865	
Bluetooth and WLAN	AP6210	
Camera (front and back)	5 MP Autofocus Back Camera (OV2720 or 5640) / 0.3 MP Front Camera	
RFID (optional)	HF 13.56Mhz (ISO14443/15693) NXP PN532	
G-Sensor	Yes, default	
Light Sensor	Yes, default	
Gyroscope	Yes, default	
Magnetometer (optional)	Yes, optional	
Display	7" TFT Touch Screen (1024x600, capacitive touch)	
Memory	ROM (SLC/MLC)	4G NAND Flash
	RAM (DDR)	1GB DDR3
	Extend Slot	Micro SD Card

Antenna	Internal antenna	
LED Indicator	Two-color LED (Red/Green)	
Interface	Mini USB Connector	USB2.0 connection and power charging
	Pago pins	support serial port, USB, 12V input, ignition, eeprom
	SIM card Slot	Yes
Battery	Capacity	2600mAh
	Standby	~3-4 days
	Operating Time	~3 hours
IP standard	IP54	

## Software

Operating System	Android version 4.4
Android Applications	TBD
Navigation Software	TBD

## Packaging Details

1pc main unit and 1pc cradle
------------------------------

### Alright-IT GmbH

Schwalbenrainweg 30a  
D-63741 Aschaffenburg  
Phone: +49 (0) 6021. 444 91 90  
Fax: +49 (0) 6021. 459 09 81  
E-Mail: [info@alright-it.com](mailto:info@alright-it.com)  
Internet: [www.alright-it.com](http://www.alright-it.com)